

8-port sector antenna, 2x 694–960, 2x 1427-1518 and 4x 1695–2690 MHz, 65° HPBW, 4x RET

- Includes 2-Ports which support operation over 1427-1518 MHz (including 1400 MHz "L-Band" applications in Europe)
- All Internal RET actuators are connected in "Cascaded SRET" configuration
- Uses the 4.3-10 connector which is 40 percent smaller than the 7-16 DIN connector

#### This product will be discontinued on: March 30, 2024

### General Specifications

Antenna Type	Sector
Band	Multiband
Grounding Type	RF connector inner conductor and body grounded to reflector and mounting bracket
Performance Note	Outdoor usage
Radome Material	Fiberglass, UV resistant
Reflector Material	Aluminum
RF Connector Interface	4.3-10 Female
RF Connector Location	Bottom
RF Connector Quantity, high band	6
RF Connector Quantity, low band	2
RF Connector Quantity, total	8

#### Remote Electrical Tilt (RET) Information

RET Interface	8-pin DIN Female   8-pin DIN Male
RET Interface, quantity	1 female   1 male
Input Voltage	10-30 Vdc
Internal RET	High band (3)   Low band (1)
Power Consumption, idle state, maximum	2 W
Power Consumption, normal conditions, maximum	13 W
Protocol	3GPP/AISG 2.0 (Single RET)

Page 1 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023



# RYVV-65B-R4


#### Dimensions

Width	350 mm   13.78 in
Depth	208 mm   8.189 in
Length	1828 mm   71.969 in
Net Weight, without mounting kit	25 kg   55.115 lb

(Sizes of colored boxes are not

true depictions of array sizes)

# Array Layout



Array	Freq (MHz)	Conns	<b>RET</b> (SRET)	AISG RET UID
R1	694-960	1-2	1	ANxxxxxxxxxxxxxx1
G1	1427-1518	3-4	2	ANxxxxxxxxxxxxxx2
Y1	1695-2690	5-6	3	ANxxxxxxxxxxxxxXXXXXXXXXXXXXXXXXXXXXXXX
Y2	1695-2690	7-8	4	ANxxxxxxxxxxxxxx4

Port Configuration

Bottom

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023





# **Electrical Specifications**

Impedance	50 ohm
Operating Frequency Band	1427 – 1518 MHz   1695 – 2690 MHz   694 – 960 MHz
Polarization	±45°
Total Input Power, maximum	800 W @ 50 °C

# **Electrical Specifications**

Frequency Band, MHz	694-790	790-890	890-960	1427-151	8 1695–192	0 1920–218	0 2300-250	0 2500-2690
Gain, dBi	15.1	15.7	15.9	16	17.7	18.5	18.8	18.5
Beamwidth, Horizontal, degrees	67	65	63	66	60	60	62	63
Beamwidth, Vertical, degrees	11.8	10.6	9.8	7	5.5	5	4.4	4.1
Beam Tilt, degrees	2-14	2-14	2-14	2-12	2-12	2-12	2-12	2-12
USLS (First Lobe), dB	16	17	16	17	16	17	17	16
Front-to-Back Ratio at 180°, dB	31	33	34	31	31	36	35	31
Isolation, Cross Polarization, dB	28	28	28	28	28	28	28	28
Isolation, Inter-band, dB	30	30	30	28	30	30	30	30
VSWR   Return loss, dB	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0

Page 3 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023

**COMMSCOPE**°

# RYVV-65B-R4

PIM, 3rd Order, 2 x 20 W, dBc	-150	-150	-150	-150	-150	-150	-150	-150
Input Power per Port at 50°C, maximum, watts	300	300	300	250	250	250	200	200

# Electrical Specifications, BASTA

Frequency Band, MHz	694-790	790-890	890-960	1427-151	8 1695–192	0 1920–218	0 2300–250	0 2500-2690
Gain by all Beam Tilts, average, dBi	14.9	15.5	15.7	15.8	17.3	18.1	18.5	18.2
Gain by all Beam Tilts Tolerance, dB	±0.3	±0.4	±0.4	±0.4	±0.7	±0.6	±0.5	±0.4
Gain by Beam Tilt, average, dBi	2 °   14.9 8 °   14.9 14 °   14.7	2 °   15.5 8 °   15.6 14 °   15.2	2 °   15.8 8 °   15.8 14 °   15.3	2 °   15.8 7 °   15.9 12 °   15.8	2 °   17.1 7 °   17.3 12 °   17.2	2 °   17.9 7 °   18.2 12 °   18.0	2 °   18.3 7 °   18.6 12 °   18.3	2 °   18.1 7 °   18.3 12 °   17.8
Beamwidth, Horizontal Tolerance, degrees	±1.2	±1.8	±1.8	±4.3	±3.4	±2.5	±4.4	±4.9
Beamwidth, Vertical Tolerance, degrees	±0.8	±0.7	±0.6	±0.4	±0.4	±0.3	±0.2	±0.2
USLS, beampeak to 20° above beampeak, dB	16	17	16	17	15	16	16	15
Front-to-Back Total Power at 180° ± 30°, dB	25	24	24	24	27	27	28	26
CPR at Boresight, dB	20	21	21	15	19	22	21	20
CPR at Sector, dB	11	10	11	6	10	7	7	5

# Mechanical Specifications

Wind Loading @ Velocity, frontal	301.0 N @ 150 km/h (67.7 lbf @ 150 km/h)
Wind Loading @ Velocity, lateral	254.0 N @ 150 km/h (57.1 lbf @ 150 km/h)
Wind Loading @ Velocity, maximum	638.0 N @ 150 km/h (143.4 lbf @ 150 km/h)
Wind Loading @ Velocity, rear	319.0 N @ 150 km/h (71.7 lbf @ 150 km/h)
Wind Speed, maximum	241 km/h (150 mph)

### Packaging and Weights

Width, packed	456 mm   17.953 in
Depth, packed	357 mm   14.055 in
Length, packed	1975 mm   77.756 in
Weight, gross	38.5 kg   84.878 lb

### Regulatory Compliance/Certifications

Agency

Classification

Page 4 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023



# RYVV-65B-R4

CE	Compliant with the relevant CE product directives
CHINA-ROHS	Above maximum concentration value
ISO 9001:2015	Designed, manufactured and/or distributed under this quality management system
ROHS	Compliant/Exempted
UK-ROHS	Compliant/Exempted
( ( 🐠 🕵	

### Included Products

9001

**BSAMNT-3** 

Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.

### \* Footnotes

**Performance Note** Severe environmental conditions may degrade optimum performance

Page 5 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023

